

Efisiensi pada Duo.



S1

Komunikasi Bisnis
Radio Dua Arah



DESIGN
AWARD
2024



Desan
minimalis



Tombol PTT depan dan
samping untuk
efisiensi
ganda



Efisiensi jangkauan
dalam ruangan
lebih dari 10.000
meter Persegi



Waktu kerja
16 jam



Manajemen
aplikasi
Hytera Radio



AirClone yang
mudah dan cepat



Pengisian daya
cepat Tipe-C



Skenario Aplikasi



Pusat Perbelanjaan



Toko



Gudang



Swalayan

Spesifikasi

Informasi Umum	
Model	HYT-S31/HYT-S31 LF
Rentang Frekuensi	400-470 MHz (Unit Utama) /446 MHz
Analog/Digital	Analog
Kapasitas Channel	48
Kapasitas Zona	3
Tegangan Operasi	3.8V (Rated)
Baterai	2200mAh Li-Polymer
Daya ahan Baterai (5/5/90 Siklus Kerja, Daya Pancar)	16 hrs (3W) / 22 hrs (1W)
Dimensi (TxLxK)	108*53*20mm (tanpa Antena)
Berat (dengan Baterai dan Antena)	146 g (tanpa sabuk Klip); 135 g (tanpa sabuk Klip)
BT	BLE (hanya data) 5.1
Receiver	
Sensitifitas	0.14μV
Ukuran Daya Output Audio	0.5W
Pemancar	
Daya Output	400-470 MHz:1W/3W(low/high); 446 MHz: 0.5W
Respon Audio	+1 to -3dB
Distorsi Audio	≤3%
Lingkungan Penggunaan	
Suhu Pengoperasian	-10°C~ +55°C
Suhu Penyimpanan	-30°C ~ +70°C
Anti-Statís	±4kV (Kontak) ±8kV (Udara)

Aksesoris

● Standar ● Opsional	
 Antena (400-440 / 430-470 MHz)	 Baterai
 Klip Sabuk	 Tali
 Antena (9cm, 400 - 470 MHz)	 Kabel Pengisian Daya USB Tipe-C
 Pengisi daya 8-slot	 Earphone
 Adapter	



PT. Hytera Communications Indonesia

Tel:+62212952 7172

Email: info@hytera.co.id

Website: www.hytera.com/id

Address: The East Building, 38th floor, Mega Kuningan, Jakarta 12950, Indonesia



Facebook



Instagram



LinkedIn



Youtube

Hytera retains right to change the product design and specification. Should any printing mistake occur, Hytera doesn't bear relevant responsibility. Little difference between real product and product indicated by printing materials will occur by printing reason.

HYT, Hytera are registered trademarks of Hytera Communications Corp., Ltd.
©2024 Hytera Communications Corp., Ltd. All Rights Reserved.